

NONLINEAR QUASICLASSICS AND THE PAINLEVÉ EQUATIONS

Vadim L. Vereschagin*

Irkutsk Computing Centre, P.O.Box 1233, Irkutsk
664033, RUSSIA

February 9, 2008

1. INTRODUCTION

A century-old history of calculation of asymptotics for solutions to Painlevé equations (usually denoted P_j , $j=1,2,\dots,6$) as their variable x tends to infinity was started by pioneer works by Painlevé, Gambier and Boutroux [1]. In 1980-1981 papers by Jimbo, Miwa and Flashka, Newell [2] initiated the so-called Isomonodromy Deformation Method (IDM) which afterwards has given remarkable progress in this direction for P_1 , P_2 , and P_3 . Successful attempts to apply the Whitham-like method connected with use of different-scaled variables were accomplished in papers [3]. This way yields leading term of the asymptotic series in form of "modulated" elliptic function (Weierstrass $\wp$ -function for P_1 or Jacobi sine for P_2) such that parameters determining it depend on x in force of certain algebraic or differential equation. At last, the Whitham approach in its "classical" interpretation was applied to P_1 by Novikov, Dubrovin, Moore, Krichever [5]. These authors obtained certain ODE usually referred to as "Whitham" or "modulation" equations. In paper [6] solutions of Discrete Painlevé-1 eq. were investigated from this point of view. The main goal of this paper is to generalize ideas of the latter method and expand them to the remaining Painlevé eqs.

2. IDEOLOGY OF THE METHOD

*Supported by ISF Grant RK 2000

Painlevé eqs are known to be integrable nonlinear ODE's. Probably, the most explicit illustration of this fact is existence of commutative matrix representation

$$\partial_\lambda L_j - \partial_x A_j + [L_j, A_j] = o, \quad j = 1, 2, \dots, 6, \quad (1)$$

where $\partial_x = \frac{\partial}{\partial x}$, $L_j = L_j(u, u', x, \lambda)$, $A_j = A_j(u, u', x, \lambda)$ are 2×2 matrices rationally depending on spectral parameter λ so that j -th Painlevé eq. $u'' - P_j(u, u', x) = 0$ is equivalent to (1). The matrices L_j , A_j are listed, for example, in [2].

Introduce now variable X and change all variables x explicitly entering L_j , A_j to X : $L_j = L_j(u, u', X, \lambda)$, $A_j = A_j(u, u', X, \lambda)$.

Proposition 1. Let ϵ be some real positive number. Then system

$$\epsilon \partial_\lambda L_j - \partial_x A_j + [L_j, A_j] = 0 \quad (2)$$

is equivalent to system

$$\begin{aligned} \partial_x X &= \epsilon \\ u'' - P_j(u, u', X) &= o \end{aligned} \quad (3)$$

Proposition 2. Solution of eq. (2) while $\epsilon = 0$ and $X = \text{const}$ is

$$u_0(x) = f_j(\tau + \Phi; \overrightarrow{a}) \quad (4)$$

where $\tau = xU$; f_j are periodic functions which can be represented in terms of Weierstrass or Jacobi elliptic functions (see [7]) for any of the six Painlevé eqs. $U = U(X)$, $\Phi = \Phi(X)$; $\overrightarrow{a}(X)$ are parameters determining the elliptic function f_j .

Suppose now ϵ to be small and positive. We shall look for solutions of (3) as formal series in ϵ :

$$u(x) = u_0(x) + \epsilon u_1(x) + \dots \quad (5)$$

so that parameters determining the elliptic functions $u_0 = f_j$ obey some special ODE called "Whitham" or "modulation" system. Thus, we look for the leading term of (5) in form $u_0(\tau, X) = f_j\left(\frac{S(X)}{\epsilon} + \Phi(X); \overrightarrow{a}(X)\right)$, where $\partial_X S = U$. The Whitham system can be easily derived from eq. (2) by simple change $\partial_x \rightarrow U \partial_\tau + \epsilon \partial_X$ and averaging in τ :

$$\partial_X \det A_j = \overline{a_{22} \partial_\lambda l_{11}} + \overline{a_{11} \partial_\lambda l_{22}} - \overline{a_{12} \partial_\lambda l_{21}} - \overline{a_{21} \partial_\lambda l_{12}} \quad (6)$$

where $A_j = (a_{mn})$, $L_j = (l_{mn})$, $m, n = 1, 2$; bar means averaging over period of the elliptic function (4).

Proposition 3. There exists only unique coefficient in the polynomial $\det A_j$ whose dynamics in X is non-trivial. Denote this coefficient F_j . Therefore the Whitham system can be written out as a single first-order ODE on F_j .

Corollary. The simplest way to find elliptic ansatz is to solve equations

$$F_j = \text{const}_1, X = \text{const}_2 \quad (7)$$

Proposition 4. The Whitham system induces formal condition

$$u_0'' - P_j(u_0, u_0', x) = O(\epsilon)^1$$

Obviously, the scaling transformation $x \rightarrow \epsilon x$ induces $\partial_x X = \epsilon \rightarrow \partial_x X = 1$ in (3), which provides the following proposition:

Proposition 5. The function u_0 specified by (4) and (6) yields leading term of asymptotic series for solution of appropriate Painlevé equation as x tends to infinity.

3. CONCRETE CALCULATIONS.

$$P_1 : u'' - 3u^2 - x = 0$$

$$\det A_1 = 16\lambda^3 + 4X\lambda - F_1, \text{ where } F_1 = (u')^2 - 2u^3 - 2Xu; \partial_X \det A_j = 2\bar{u} + 4\lambda \Rightarrow$$

$\partial_X F_1 = -2\bar{u} = -2\eta/\omega = 2e_1 + 2(e_3 - e_1)\frac{E}{K}$, where K, E are complete elliptic integrals:

$$K = \int_0^1 \frac{dz}{\sqrt{(1-z^2)(1-k^2z^2)}}, \quad E = \int_0^1 \sqrt{\frac{1-k^2z^2}{1-z^2}} dz, \quad k^2 = \frac{e_2 - e_3}{e_1 - e_3}; \quad e_1, e_2, e_3 \text{ are}$$

roots of the polynomial $R_3(z) = 4z^3 - g_2z - g_3$, $g_2 = -X$, $g_3 = -\frac{1}{4}F_1$.

$$u_0 = 2\wp(x + \Phi; g_2, g_3).$$

$$P_2 : u'' - 2u^3 - ux = 0^2$$

$$\det A_2 = 16\lambda^4 + 8X\lambda^2 + X^2 - 4F_2, \text{ where } F_2 = (u')^2 - u^4 - Xu^2;$$

¹This condition makes rigorous sense only for smooth function u . However, the method describes singular solutions as well.

²Case with additional constant can be investigated in the same way

$$\begin{aligned} \partial_X \det A_2 &= 8\lambda^2 + 2X + 4\overline{u^2} \Rightarrow \partial_X F_2 = -\overline{u^2} = 2\frac{\eta}{\omega} - e_m = X \left(\frac{1}{2} - \frac{1}{2-k^2} \frac{E}{K} \right), \\ \text{where } k^2 &= \frac{X}{2F_2} (X \mp \sqrt{X^2 - 4F_2}) - 1; \\ u_0 &= \sqrt{-\frac{1}{2}(x \mp \sqrt{x^2 - 4F_2})} \operatorname{sn} \left(\frac{x}{\sqrt{2}} \sqrt{-x \pm \sqrt{x^2 - 4F_2}} + \Phi; k \right), \quad \operatorname{sn} \text{ is Jacobi sine.} \end{aligned}$$

$$\begin{aligned} P_3 : \quad u'' + \frac{1}{x}u' + \sin u &= 0 \\ \lambda^4 \det A_3 &= \frac{\lambda^4 X^4}{256} + \frac{\lambda^2 X^2}{8} F_3 + 1, \text{ where } F_3 = \frac{(u')^2}{2} - \cos u; \\ \partial_X F_3 &= -\frac{2}{X} (F_3 + \overline{\cos u}) = \frac{1}{Xk^2} \left(k^2 - 1 + 2\frac{E}{K} \right), \quad k^2 = \left(-F_3 \pm \sqrt{F_3^2 - 1} \right)^2; \\ u_0 &= -2i \log \left(k \operatorname{sn} \left(\frac{ix}{2k} + \Phi; k \right) \right) \end{aligned}$$

$$\begin{aligned} P_4 : \quad u'' &= \frac{(u')^2}{2u} + \frac{3u^3}{2} + 4xu^2 + u(a - 4d + 2x^2) - \frac{a^2}{4u}, \text{ where } a, d \text{ are arbitrary parameters.} \\ \det A_4 &= -\frac{\lambda^6}{4} - X\lambda^4 - (d - a + X^2)\lambda^2 - F_4 - \frac{d^2}{\lambda^2}, \\ F_4 &= \frac{(u')^2}{4u} - \frac{u^3}{4} - Xu^2 - u \left(X^2 + \frac{a}{2} - 2d \right) + X(2d - a) - \frac{a^2}{4u}, \\ \partial_X \det A_4 &= -\lambda^4 - 2X\lambda^2 + \overline{u^2} + 2X\overline{u} + a - 2d \Rightarrow \partial_X F_4 = -\overline{u^2} - 2X\overline{u} - a + 2d \\ \text{and } u_0 &= \pm U [\zeta(Ux + \Phi_1) - \zeta(Ux + \Phi_2)] \pm U \zeta(\Phi_2 - \Phi_1) - X, \text{ parameters } U, \Phi_2 - \Phi_1 \text{ can be derived from (7). The Whitham eq. looks too large to be written out explicitly.} \end{aligned}$$

$$\begin{aligned} P_5 : \quad u'' &= \frac{3u-1}{2u(u-1)} (u')^2 - \frac{u'}{x} + \mu \frac{u}{x} - \mu^2 \frac{u(u+1)}{2(u-1)}, \quad \mu \text{ is a parameter;} \\ \det A_5 &= -4X^2 - \frac{F_5}{\lambda(\lambda-1)}, \quad F_5 = \frac{X^2}{4u(u-1)^2} \left[(u')^2 - 2uu'(\mu-4) + u^2\mu(\mu-8) \right]; \\ \partial_X \det A_5 &= -8X + \frac{4\overline{z}}{\lambda(\lambda-1)}, \text{ where } z = \frac{X(\mu u - u')}{2(u-1)^2} \Rightarrow \partial_X F_5 = -4\overline{z}; \\ u_0 &= \frac{U^2 x^2}{F_5} [\wp(Ux + \Phi_1) + \wp(Ux + \Phi_2)] \\ &+ \frac{U^3 x^4 (\mu-4)}{F_5(3F_5 - U^2 x^2)} [\zeta(Ux + \Phi_1) - \zeta(Ux + \Phi_2)] + V, \\ \text{parameters } U, \Phi_1 - \Phi_2, V &\text{ can be derived from (7).} \end{aligned}$$

$$\begin{aligned} P_6 : \quad u'' &= \frac{1}{2} \left(\frac{1}{u} + \frac{1}{u-1} + \frac{1}{u-x} \right) (u')^2 - \left(\frac{1}{x} + \frac{1}{x-1} + \frac{1}{u-x} \right) u' \\ &+ \frac{u(u-1)(u-x)}{x^2(x-1)^2} \left[\alpha + \beta \frac{x}{u^2} + \gamma \frac{x-1}{(u-1)^2} + \delta \frac{x(x-1)}{(u-x)^2} \right], \\ \alpha, \beta, \gamma, \delta &\text{ are parameters;} \\ \lambda[(\lambda-1)(\lambda-x)]^2 \det A_6 &= k_1 k_2 \lambda^3 + F_6 \lambda^2 + S_1 \lambda + S_0; \end{aligned}$$

One can determine F_6 and the elliptic ansatz from the following constraint:

$$(u')^2 x^2 (x-1)^2 + u' a_0 + (k_1 - k_2)^2 u^4 + a_3 u^3 + a_2 u^2 + a_1 u + \theta_0^2 x^2 = 0,$$

where:

$$\begin{aligned} \frac{1}{2}a_0 &= u^2 x(x-1)(k_1 + k_2) + ux [x^2(\theta_0 + \theta_1) + x(\theta_2 - \theta_1) - \theta_0 - \theta_2] - \theta_0 x^3 + \theta_0 x^2, \\ \frac{1}{2}a_3 &= 4k_2(k_1 - k_2)(x+1) + (3k_2 - k_1)[x(\theta_0 + \theta_1) + \theta_0 + \theta_2] - 2F_6, \\ a_2 &= x^2[(\theta_0 + \theta_1)(\theta_0 + \theta_1 + 4k_1 - 4k_2) + 4k_2(2k_2 - k_1)] + 2x[10k_2^2 - 6k_1k_2 - 2k_1^2 - 4k_1\theta_0 \\ &\quad + \theta_2\theta_1 + 2F_6] + 4k_2(2k_2 - 2k_1) + (\theta_0 + \theta_2)(\theta_0 + \theta_2 + 4k_1 - 4k_2) + 4F_6, \\ \frac{1}{2}a_1 &= x^2[(\theta_0 + \theta_1)(2k_2 - 2k_1 - \theta_0) + 2k_2(k_1 - 2k_2)] + x[(\theta_0 + \theta_2)(2k_2 - 2k_1 - \theta_0) + 2k_2(k_1 - 2k_2)] - 2F_6; \\ k_1 + k_2 &= -(\theta_0 + \theta_1 + \theta_2), \quad k_1 - k_2 = \theta_\infty, \quad \alpha = \frac{1}{2}(\theta_\infty - 1)^2, \quad \beta = -\frac{1}{2}\theta_0^2, \\ \gamma &= \frac{1}{2}\theta_1^2, \quad \delta = \frac{1}{2}(1 + \theta_2^2); \\ \partial_X F_6 &= -2k_1k_2 + z_2(k_1 - k_2) + \theta_2(z_2 - k_2) + \frac{(z_0 + \theta_0)z_0(u-x)}{u(x-1)} - \frac{(z_1 + \theta_1)z_1(u-x)}{x(u-1)}, \text{ where} \\ z_0 &= \frac{u}{x\theta_\infty} \{u(u-1)(u-x)z^2 + [\theta_1(u-x) + x\theta_2(u-1) - 2k_2(u-1)(u-x)]z + k_2^2(u-x-1) - k_2(\theta_1 + x\theta_2)\}, \\ z_1 &= -\frac{u-x}{(x-1)\theta_\infty} \{u(u-1)(u-x)z^2 + [(\theta_1 + \theta_\infty)(u-x) + x\theta_2(u-1) - 2k_2(u-1)(u-x)]z + k_2^2(u-x) - k_2(\theta_1 + x\theta_2) - k_1k_2\}, \\ z_2 &= \frac{u-x}{x(x-1)\theta_\infty} \{u(u-1)(u-x)z^2 + [\theta_1(u-x) + x(\theta_2 + \theta_\infty)(u-1) - 2k_2(u-1)(u-x)]z + k_2^2(u-1) - k_2(\theta_1 + x\theta_2) - xk_1k_2\}, \\ z &= \frac{u'x(x-1) - \theta_0(u-1)(u-x) - \theta_1u(u-x) - \theta_2u(u-1)}{2u(u-1)(u-x)} \end{aligned}$$

References

- [1] P.Painlevé. - Acta Math., 1902, v.25, p.1-86; B.Gambier. - Acta Math., 1910, v.33, p.1-55;
P.Boutroux. - Ann. Sci. l'école Norm. Supér., 1913, v.30, p.255-376
- [2] M.Jimbo, T.Miwa. - Physica D, 1981, v.2D, #3, p.407-448; H.Flaschka, A.C.Newell. - Commun. Math. Phys., 1980, v.76, #1, p.67-116
- [3] N.Joshi, M.D.Kruskal. - Phys. Lett. A, 1988, v.130, #3, p.129-137

- [4] V.Yu.Novokshenov. - DAN SSSR, 1990, v.311, #2, p.288-291 (Russian)
- [5] G.Moore. - Commun. Math. Phys., 1990, v.133, #3, p.261-304;
S.P.Novikov. - Funkz. Analiz i ego Pril., 1990, v.24, #4, p.43-53;
I.M.Krichever. - On Heisenberg Relations for the Ordinary Linear Differential Operators. - Preprint IHES, Bur-Sur-Yvette, 1990
- [6] V.L.Vereschagin. - Physica D 95 (1996) 268-282
- [7] H.Bateman, A.Erdelyi. Higher Transcendental Functions. - 3. McGraw-Hill, New York (1955)